

## TRMS AC/DC LOW CURRENT CLAMP METER (1mA)

243

### Features :

- 1 mA Current Resolution
- True-RMS Measurement For All Applications
- AC+DC True RMS Measurements
- Built-in LED Work Light
- Backlight Function
- Data Hold Function
- Zero Function
- Auto Power Off/ Auto ranging



### Specifications :

Function	Range	Resolution	Accuracy
DC/AC mA	4000mA	1mA	± 2.0% rdg ± 5 dgts
DC/AC A	40.00A / 200.0A	0.01A~0.1A	± 2.0% rdg ± 5 dgts
AC+DC mA/A	4000mA / 40.00A / 200.0A	1mA~0.1A	± 2.5% rdg ± 5 dgts
DCV/ACV	6.000V / 60.00V / 600.0V	0.001V~0.1V	± 1.0% rdg ± 2 dgts
AC+DC V	6.000V / 60.00V / 600.0V	0.001V~0.1V	± 1.2% rdg ± 5 dgts
Capacitance	1.000uF / 10.00uF / 100.0uF / 1000uF	0.001uF~1uF	± 3% rdg ± 8 dgts
Diode	2.000V	0.001V	± 2% rdg ± 5 dgts
Ohms	600.0Ω / 6.000KΩ / 60.00KΩ / 600.0KΩ	0.1Ω~0.1KΩ	±1% rdg ± 3 dgts
•)))_Active Sound Level	< 100Ω		

Display : 4 digital Liquid display, Maximum reading 6000  
 Sampling Rate : 2 times/sec  
 Battery : 1.5V size AAA battery x 2  
 Dimensions : 232 x 72 x 35 mm  
 Weight : 230 g  
 Maximum Jaw Opening : ø 20 mm

### Standard Delivery :

- Basic Instrument with Battery
- Test Lead
- Carrying Case
- Traceable Calibration Certificate
- Instruction Manual

### Optional :

- Calibration Certificates are issued in Accordance with our Scope as granted by NABL per ISO/IEC 17025:2017 Standards

Marketed by...



**NAGMAN INSTRUMENTS AND ELECTRONICS PRIVATE LIMITED.**

Chennai-Bangalore National Highway, Nazarethpet P.O., Chembarambakkam,  
Chennai – 600 123. INDIA.

**AN ISO 9001:2015  
CERTIFIED COMPANY**

Since 1972

**Domestic Sales Phone :** 044 – 66777020, 005, 021, 024.

**E-Mail :** mktgchennai@nagman.com

**Export Sales Phone :** +91-44-66777025.

**E-Mail :** exports@nagman.com

[www.nagman.com](http://www.nagman.com)