

TRMS AC/DC LOW CURRENT CLAMP METER (1mA)

243

Features :

- 1 mA Current Resolution
- True-RMS Measurement For All Applications
- AC+DC True RMS Measurements
- Built-in LED Work Light
- Backlight Function
- Data Hold Function
- Zero Function
- Auto Power Off/ Auto ranging



Specifications :

Function	Range	Resolution	Accuracy
DC/AC mA	4000mA	1mA	± 2.0% reading ± 5 digits
DC/AC A	40.00 / 100.0 / 200.0A	0.01A~0.1A	± 2.0% / ± 4.0% / ± 8.0% reading ± 5 digits
AC+DC mA/A	4000mA / 200.0A	1mA~0.1A	± 2.5% reading ± 5 digits
DCV/ACV	6.000V / 60.00V / 600.0V	0.001V~0.1V	± 1.0% reading ± 2 digits
AC+DC V (True RMS)	6.000V / 60.00V / 600.0V	0.001V~0.1V	± 1.2% reading ± 5 digits
Capacitance	1.000uF / 10.00uF / 100.0uF / 1000uF	0.001uF~1uF	± 3% reading ± 8 digits
Diode	2.000V	0.001V	± 2% reading ± 5 digits
Ohms	600.0Ω / 6.000KΩ / 60.00KΩ / 600.0KΩ	0.1Ω~0.1KΩ	±1% reading ± 3 digits
•)))_Active Sound Level	< 100Ω		

Display : 4 digital Liquid display
 Sampling Rate : 2 times/sec
 Battery : 1.5V size AAA battery x 2
 Dimensions : 232 x 72 x 35 mm
 Weight : 230 g
 Maximum Jaw Opening : ø 20 mm

Standard Delivery :

- Basic Instrument with Battery
- Test Lead
- Carrying Case
- Traceable Calibration Certificate
- Instruction Manual

Optional :

- Calibration Certificates are issued in Accordance with our Scope as granted by NABL per ISO/IEC 17025:2017 Standards

Manufactured by



Since 1972

NAGMAN INSTRUMENTS AND ELECTRONICS PRIVATE LIMITED

AN ISO 9001:2015 CERTIFIED COMPANY

170/1a2, Chennai Bangalore Highway Road, Sembarambakkam, Chennai – 600 123. INDIA.

Phone - Domestic Sales 044-6677 7024, 044-6677 7005 Email : mktgchennai@nagman.com

Phone - Export Sales +91-44-6677 7025. Email : exports@nagman.com

www.nagman.com

